



## T-VER-8044-100 Sensor

### Veris 480 V, 100 Amp Kilowatt Transducer Sensor

The Veris AC Kilowatt Transducer incorporates three split-core AC current sensors and three voltage leads and outputs a signal proportional to kilowatts of power (demand). Accepting an input primary voltage of 480 Volts AC rms, this transducer requires a FlexSmart Analog Module. Because these sensors tie directly into the line, they should be used only by qualified personnel. NOTE: Not recommended for use with variable frequency drives.



Requires analog port selection during U30 system configuration and use of a S-FS-CVIA when using the H22-001 data logger. When using a U12 data logger, this sensor requires a 4-20mA input cable (CABLE-4-20mA) and external power provided by an AC adapter (AC-SENS-1).

#### Supported Measurements:

Kilowatts (kW)

#### Key Advantages:

- Split-core installation eliminates the need to remove conductors
- Self-contained 0 to 100 AMP current transducer for 1- or 3-phase power monitoring
- Precision meter electronics

## T-VER-8044-100 Sensor Specifications

**Includes:** 3 100 Amp Split-Core Current Transformers (CT)

**Input primary voltage:** 480 Volts AC rms

**Accuracy:**  $\pm 1\%$  per ANSI (C12.1) (from 10 to 100% of CT rating)

**Number of phases monitored:** 3

**Frequency:** 50/60 Hz

**Internal isolation:** 2000 VAC rms

**Insulation class:** 600 VAC rms

**Operating temp range:** 0 to 60°C (32° to 140°F)

**Operating humidity range:** 0 to 95% RH, non-condensing

**Output signal to FlexSmart:** 4-20mA

**Supply powered (current loop):** 9-30 VDC, 30mA max

**Current transformer:** 100 Amp AC

3.8cm x 3.2cm (1.5 in. x 1.25 in.)

**Dimensions of each CT:** 10.7cm x 12.1cm x 2.9cm (4.2 in. x 4.75 in. x 1.13 in.)

**Number of data channels:** 1

To download the manual from Veris click [here](#).

1.800.561.8187

www.itm.com

information@itm.com

products and brand names may be trademarks or registered trademarks of their respective owners. Patented technology (U.S. Patent 6,826,664)