

# CLAMP-ON METERS

## 400 & 600 SERIES BLUETOOTH EDITION

### POWER AND HARMONIC METERS

## MODELS 407 & 607

Now available with Android™ mobile application

## SPECIFICATIONS

MODELS	407 TRMS	607 TRMS
<b>ELECTRICAL</b>		
Current AC (rms)	1000 A	2000 A
Current DC	1500 A	3000 A
Current AC+DC	1500 A Peak	3000 A Peak
Voltage AC (rms)	1000 V	
Voltage DC	1000 V	
Voltage AC+DC	1000 V	
Ohms	100 kΩ	
Continuity (Buzzer)	Yes (< 40 Ω)	
Total Harmonic Distortion	Yes	
Individual Harmonics (to 25 <sup>th</sup> )	Yes	
Single- and 3-Phase Real Power (AC, DC, AC/DC)*	1000 kW	
Single- and 3-Phase Reactive Power (AC, DC, AC/DC)*	1000 kvar	2000 kvar
Single- and 3-Phase Apparent Power (AC, DC, AC/DC)*	1000 kVA	2000 kVA
Voltage Frequency	20 kHz	
Current Frequency	2 kHz	1 kHz
Power Factor	Yes	
THD-r / THD-f	Yes / Yes	
Auto AC/DC	Yes (V & A)	
Auto Power OFF	Yes	
Hold Button	Yes	
Backlight Button	Yes	
Min/Max Button	Yes	
True InRush® Function	Yes	
Peak ± Function	Yes	
Harmonics Function	Yes	
Rec (Record) Function	Yes	
Wireless BT (Bluetooth) Function	Yes	
Record (Recordings)	1000	
Hz Button	Yes	

\*Three-phase measurements assume balanced load  
Consult factory for NIST Calibration prices

## PRODUCT INCLUDES

Hard carrying case, set of (2) color-coded silicone test leads, test probes and alligator clips, Bluetooth USB adapter, (4) 1.5 V AA batteries, safety information sheet, and USB drive supplied with DataView® software and user manual.



## FEATURES

- 1000 V CAT IV Rated
- UL 94 VI flame retardant self-extinguishing
- 10,000-count blue electroluminescent backlit display
- Measures up to 1000 VAC (1400 V peak), 1000 Vdc and AC+DC with resolution to 10 mV
- Measures up to 2000 AAC and 3000 AAC (Model 607)
- Measures single- and three-phase power (real, reactive and apparent) up to 3 MW with resolution to 1 W
- Measures frequency to 20 kHz with 0.1 Hz resolution
- Auto selects AC or DC measurement
- True InRush® current measurement with 100 mS capture
- Measures harmonics up to the 25<sup>th</sup>
- Records up to 1000 measurements
- Bluetooth communication (communicates up to 30 ft)
- Includes FREE DataView® software for download and report generation
- Jaw opening up to  
1.89 in (48 mm) (400 series)  
2.36 in (60 mm) (600 series)

## CATALOG NO. DESCRIPTION

2139.51	Power Clamp-On Meter Model 407 (TRMS, 1000 VAC/DC, 1000 AAC/1500 ADC, Ohms, Continuity, Energy, Harmonics, Power, THD, Recording)
2139.61	Power Clamp-On Meter Model 607 (TRMS, 1000 VAC/DC, 2000 AAC/3000 ADC, Ohms, Continuity, Energy, Harmonics, Power, THD, Recording)



Vol. 23 Rev.00 02/2023

Technical Assistance (800) 343-1391

www.aemc.com

9

1.800.561.8187

www.itm.com

information@itm.com

# CLAMP-ON METERS

## SELECTION GUIDE

Models	Catalog Number	Type	AC Current	AC Voltage	DC Current	DC Voltage	Resistance ( $\Omega$ )	Continuity	Frequency (Hz)		Jaw Size	Dimensions
									Current	Voltage		
205	2139.40	AC/DC TRMS	600 A	1000 V	900 A	1000 V	60 k $\Omega$	< 40 $\Omega$	3 kHz	20 kHz	1.34 in (34 mm)	(8.7 x 3.1 x 1.65) in
403	2139.21	AC/DC TRMS	1000 A	1000 V	1500 A	1000 V	100 k $\Omega$	< 40 $\Omega$	2 kHz	20 kHz	1.89 in (48 mm)	(10.7 x 3.6 x 1.6) in
405	2139.50	AC/DC TRMS	1000 A	1000 V	1500 A	1000 V	100 k $\Omega$	< 40 $\Omega$	2 kHz	20 kHz	1.89 in (48 mm)	(10.7 x 3.6 x 1.6) in
407	2139.51	AC/DC TRMS	1000 A	1000 V	1500 A	1000 V	100 k $\Omega$	< 40 $\Omega$	2 kHz	20 kHz	1.89 in (48 mm)	(10.7 x 3.6 x 1.6) in
603	2139.31	AC/DC TRMS	2000 A	1000 V	3000 A	1000 V	100 k $\Omega$	< 40 $\Omega$	1 kHz	20 kHz	2.36 in (60 mm)	(11.65 x 4.37 x 1.61) in
607	2139.61	AC/DC TRMS	2000 A	1000 V	3000 A	1000 V	100 k $\Omega$	< 40 $\Omega$	1 kHz	20 kHz	2.36 in (60 mm)	(11.65 x 4.37 x 1.61) in
505	2139.82	AC/DC TRMS	400 A	600 V	400 A	600 V	600 $\Omega$	< 35 $\Omega$	400 Hz	400 Hz	1.18 in (30 mm)	(7.83 x 2.95 x 1.42) in
514	2117.70	AC/DC TRMS	1000 A	750 V	1000 A	1000 V	4000 $\Omega$	< 40 $\Omega$	10 kHz	10 kHz	1.58 in (40 mm)	(9.53 x 2.60 x 1.42) in
566*	2139.83	AC TRMS	100 A	600 V	–	600 V	600 k $\Omega$	< 45 $\Omega$	500 Hz	500 Hz	0.91 in (23 mm)	(8.27 x 3.0 x 1.32) in
CM605	7000.02	AC/DC	100 A	600 V	100 A	600 V	9999 $\Omega$	< 100 $\Omega$	500 Hz	500 Hz	0.60 in (15 mm)	(7.95 x 2.76 x 1.33) in

\*Model 566 can be found in the Leakage Current Meters & Probes on Page 80  
Consult factory for NIST Calibration prices