

Two-wire infrared thermometer for temperature measurement from –30 °C to 1000 °C (–22 °F to 1832 °F)

Features:

- Temperature range from –30 °C to 1000 °C (–22 °F to 1832 °F), measuring spots up from 1.4 mm (0.06 in) and response times up from 150 ms
- Single-piece, robust design for easy installation into your process system
- Standard two-wire interface for reliable data transfer and easy integration into a PLC
- Innovative double-laser sighting for exact marking of measurement targets
- Fast sensor parameterisation and real-time measurement via USB
- Dependable in ambient temperatures up to 85 °C (185 °F) without additional cooling
- Wide power range: 5–28 V DC



General specifications

| | |
|----------------------|--|
| Environmental rating | IP 65 (NEMA-4) front mountable at vacuum processes (up to 10 ⁻³ mbar) |
| Ambient temperature | –20 °C to 85 °C (–4 °F to 185 °F) (50 °C (122 °F) with laser ON) |
| Storage temperature | –40 °C to 85 °C (–40 °F to 185 °F) |
| Relative humidity | 10 – 95 %, non condensing |
| Vibration | IEC 68-2-6: 3 G, 11 – 200 Hz, any axis |
| Shock | IEC 68-2-27: 50 G, 11 ms, any axis |
| Weight | 600 g (21.2 oz) |

Electrical specifications

| | |
|--|--|
| Output / analog | 4 – 20 mA |
| Loop resistance | Max. 1000 Ω ¹⁾ |
| Output / alarm | 0 – 30 V / 500 mA (open collector) |
| Output / digital | Uni-/ bidirectional, 9.6 kBaud, 0/3 V Pegel, USB optional |
| Cable length (connector version only) | 3 m / 8 m / 15 m (9.8 ft / 26.2 ft / 49.2 ft) |
| Current draw (laser) | 45 mA at 5 V 20 mA at 12 V 12 mA at 24 V |
| Power supply | 5 – 30 V DC |

Measurement specifications

| | |
|--|--|
| Temperature range (scalable via software) | –30 °C to 1000 °C (–22 °F to 1832 °F) |
| Spectral range | 8 – 14 μm |
| Optical resolution (90 % energy) | 50:1 |
| System accuracy (at T _{amb} = 23 ± 5 °C) (73 ± 9 °F) | ±1 % or ±1 °C ²⁾ (±1 % or ±1.8 °F) |
| Repeatability (at T _{amb} = 23 ± 5 °C) (73 ± 9 °F) | ±0.5 % or ±0.5 °C ²⁾ (±0.5 % or ±0.9 °F) |
| Temperature resolution | 0.1 K |
| Response time (90 % signal) | 150 ms |
| Emissivity/ Gain (adjustable via sensor or software) | 0.100 – 1.100 |
| IR window correction (adjustable via software) | 0.100 – 1.000 |
| Signal processing (parameter adjustable via software) | Peak hold, valley hold, average; extended hold function with threshold and hysteresis |
| Software | optris® Compact Connect |

¹⁾ In dependence on supply voltage

²⁾ Whichever is greater

